


Fuji USER MANUAL

SAND RAMMERS

MODELS : FR-18L, -18L-2F



FR-18L



FR-18L-2F

SPECIFICATIONS

Model	Piston Diameter	Blows	Stroke	Air Consumption (At Load)	Mass	Overall Length	Air Inlet Thread Size	Air Hose Size
	mm							Hz
FR-18L	18	30	50	0.4	2.3	560~638	Rc 1/4	9.5
FR-18L-2F	18	30	50	0.4	2.50	549~627	Rc or NPT3/8	9.5

The performance figures are at 0.63MPa (6.3bar).



Refer to "The Instructions and Warning for Safety Use" enclosed in each tool box.

Fuji Industrial Technique Co.,Ltd.

2-1-14, Kamiji, Higashinari-ku, Osaka, 537-0003 Japan

Tel : 81-6-6972-2335

Fax : 81-6-6972-2380

ASSEMBLY TOOLS

ABRASIVE TOOLS

DRILLS / TAPPERS

PERCUSSIVE TOOLS

AIR MOTORS

OTHER PRODUCTS

